

PREPARATIONS

This section tells you what you have to prepare to use zacktrack.

BASIC PREPARATIONS

To operate a zacktrack mini System, some basic preparations are necessary.

Connect the zacktrack master anchor as seen in the lower picture (See also [Network](#)). Connect 5V USB-C Power supplies to the anchors and wait until they are fully charged (constant green light).

Put the trackers into the charging station and connect a 5V USB power supply. Wait until the trackers are fully charged (constant green light).

Hardware Setup Overview

Attention a zacktrack mini System is limited at 5 anchors without the master anchor!



Set up the lighting console

It is possible to set up the lighting console and the zacktrack CORE in 3 different setups depending on the conditions of the whole lighting network setup.

[Add](#) specific ZACFIXTURE channels on the lighting desk to control individual fixtures by zacktrack.

[Add](#) specific ZACTAG channels on the lighting desk to control the settings of individual actors.

Grand MA 2

[DOWNLOAD](#) of prepared GRAND MA 2 / zacktrack Fixture Types

Lighting console setup 1

The lighting desk sends e.g. Universe 1 over sACN or ArtNet → zacktrack receives this Universe, manipulates the DMX channels according to the positions of the Actors and outputs the data on a new universe e.g. Universe 11 directly to the sACN / ArtNET DMX node.



Lighting console setup 2

The lighting desk sends e.g. Universe 1 over sACN or ArtNet → zacktrack receives this Universe, manipulates the DMX channels according to the positions of the Actors and outputs the data on a new

universe e.g. Universe 11 back to the lighting desk.



Lighting console setup 3

The lighting desk sends e.g. Universe 1 Prio 100 over sACN → zacktrack receives this Universe, manipulates the DMX channels according to the positions of the Actors and outputs the data on the same universe e.g. Universe 1 Prio 101. The sACN / DMX node should always listen to the highest priority.

Note: zacktrack doesn't listen to its own universe output to prevent a sACN loop.



From:

<https://manual.zacktrack.com/> - **zacktrack**

Permanent link:

https://manual.zacktrack.com/doku.php?id=manual:mini_preparations

Last update: **2022/11/07 15:54**

