

ZACFIXTURE 3.11		
Channel Mode	DMX Value	Function
Standard		
1		ZACTAG
	0	No Assignment
	1	zacTag 1
	2	zacTag 2
	3	zacTag 3

	255	XYZ Origin
2-3		Crossfade
	0	Disable Crossfade
	1-65535	Crossfade from Console position to tracking position
4		TRANSITION TIME
	0-255	Fixture Transition Time between assignments
5-6		X-OFFSET
	0	Disable X-OFFSET
	1-32768	- 32,7 meters to 0 X-Offset
	32768	0 X-Offset
	32768-65535	0 to 32,7 meters X-Offset
7-8		Y-OFFSET
	0	Disable Y-OFFSET
	0-32768	- 32,7 meters to 0 Y-Offset
	32768	0 Y-Offset
	32768-65535	0 to 32,7 meters Y-Offset
9-10		Z-OFFSET
	0	Disable Z-OFFSET
	0-32768	- 3,27 meters to 0 Z-Offset
	32768	0 Z-Offset
	32768-65535	0 to 3,27 meters Z-Offset
11		FIXTURE MODE
	0-63	Auto-2
	64-127	Auto-6
	128-190	Auto-6M
	191-255	Tablet