

ZACFIXTURE			
Channel Mode		DMX Value	Function
Standard	Basic		
1	1		ZACTAG
		0-255	Assignment to zacTag
2-3	-		X-FADE
		0-65535	X-Fade from Console position to tracking position
4	2		TRANSITION TIME
		0-255	Fixture Transition Time between assignments
5-6	-		X-OFFSET (Change ratio in server.properties)
		0-32768	- 3,27 meters to 0 X-Offset
		32768	0 X-Offset
		32768-65535	0 to 3,27 meters X-Offset
7-8	-		Y-OFFSET (Change ratio in server.properties)
		0-32768	- 3,27 meters to 0
		32768	0 Y-Offset
		32768-65535	0 to 3,27 meters Y-Offset
9-10	-		Z-OFFSET (Change ratio in server.properties)
		0-32768	- 3,27 meters to 0 Z-Offset
		32768	0 Z-Offset
		32768-65535	0 to 3,27 meters Z-Offset
11	-		MODE
		0-63	Auto-2
		64-127	Auto-6
		128-190	Auto-6M
		191-255	Tablet

ZACTAG		
Channel	DMX Value	Function
1		HEIGHT
	0-255	Target Height
2		Speed
	0-85	Slow
	86-170	Medium
	171-255	Fast